


# GETTING TO KNOW THE BAG PHONE

# GETTING STARTED





Insert the SIM card:






Connect the Car Lighter or Wall



Socket power adaptor to the Connector Panel (the bag phone contains a battery DC Socket Mini USB External Socket Microphone for backup use):











Motorola M900BP GSM Bag Phone

Short User's Guide







## GETTING TO KNOW THE M900

### INITIAL SET-UP

### CALL MANAGEMENT

### BASIC OPERATIONS

# Voice Activation Key Large Graphics Display Menu Key Right Soft Key Mini USB Connector Left Soft Key Send Key End Key Way Navigation Key/ Volume Kevs Internet Access Voicemail Key Keypad SIM Card Tray Power Key Personal Handset

#### POWER CONTROL

Press and hold the Power Key ountil the Turning On/Off display panel lights on/off.

#### **VOLUME CONTROL**

Keys on the side of the phone to adjust the Call Volume During a call press either of the Volume Keys on the side of the phone to adjust the volume. Muting Microphone During a call, press the Right Soft Key to mute. Key Volume Press Menu Key \_\_\_\_, scroll down to settings, ring styles, ring detail, key volume.

Ring Tone Volume When no call is active, press either of the Volume

### OTHERS Letter Size

and Contrast

To enlarge characters or numbers on the display, press Menu Key \_\_\_ briefly and then press and hold Menu Key again. Display Backlight Press Menu Key and select settings. Select other settings, then initial setup, then select backlight or contrast and use 4 Way Navigation Key to adjust. Press OK to finish.

#### PHONE CALLS

Press Send Key vor press Voice Key ...... Answering a Call Press End Key or press Voice Key ...... Ending a Call Making a Call Dial the phone number including area code and press Send Key V.

#### **VOICE ACTIVATION**

Name Dialing Press Voice Key once and say the name as was recorded (see Basic Operations). Press Voice Key — twice and say the phone Number Dialing number (initial recording is not required). Speed Dial Press Voice Key — twice, say the digits of the phonebook entry and then say "pound". Press Menu Key and then press Voice Menus

(see Basic Operations).

#### RECENT CALLS

Calls

Press upper/lower arrow of the 4 Way Received/Dialed Navigation Key for received/dialed last calls.

Key \_\_\_\_. Say shortcut name as was recorded

#### **KEYPAD SHORTCUTS**

Using Shortcuts • For your own private Menu press My Menu feature, scroll down, press New and follow

instructions.

For Phonebook press Left Soft Key

 For Web Browser press and hold upper arrow of the 4 Way Navigation Key 🙆.

For Voicemail press and hold Key #1

Creating Shortcuts to your own private Menu

 Select the item you want to add; press and hold Menu Key \_\_\_\_. You'll be asked to confirm the shortcut; press Yes. Select Key Shortcut and then Voice in order to record Voice Shortcut.

 For menu shortcut activation press Menu Key and then the allocated menu number or use the voice activation feature.

#### PHONEBOOK MEMORY

Storing a New Enter the phone number and press Right Soft Key (Store), then scroll to select details: Number

Name, Number, Type and Voice Name (for voice activation). Select More if you want to create another contact under the same name. Press Left Soft Key (Done) to finish.

Enter phonebook menu, select Search, enter Advanced Search

character(s) and press OK.

Speed Dial Enter the digits from the stored phone memory entry you want to call and hold the last digit

continuously until the number dials.

\* Various phone menus and features are operator dependent





